

# Data Sheet

## High Current DC Power Supplies Models 1790, 1791, 1794, 1795 & 1796



Model 1795

Models 1790, 1791, 1794, 1795 & 1796 are cost-effective, high power, regulated DC power supplies. These linear power supplies are high power workhorses that will easily deliver clean power to your high-current circuits. Special features include the ability to set constant current with no load and remote sense to compensate for any voltage drop in load leads.

### Features & Benefits

- Constant voltage (CV) and constant current (CC) operation
- High stability and excellent regulation
- Separate output ON/OFF switch
- Remote sensing
- External analog programming interface

Specifications	1790	1791	1794	1795	1796
<b>Output Characteristics</b>					
Voltage	0-32 V	0-64 V	0-32 V	0-64 V	0-16 V
Current	0-20 A	0-10 A	0-30 A	0-15 A	0-50 A
Max. Power	640 W	640 W	960 W	960 W	800 W
<b>Constant Voltage Mode</b>					
Line Regulation	< ±0.01% ± 2 mV				
Load Regulation	< ±0.01% ± 2 mV				
Ripple and Noise (20 Hz - 20 MHz)	< 1mV rms				
<b>Constant Current Mode</b>					
Line Regulation	< ±0.05% ± 10 mA				
Load Regulation	< ±0.05% ± 10 mA				
Ripple and Noise (20 Hz - 20 MHz)	3 mA rms		6 mA rms		3 mA rms
<b>General</b>					
Stability (Total drift within 8 hours after warm up under constant line, load, and temperature)	± 0.2% ± 10 mV in CV mode ± 0.5% ± 10 mA in CC mode				
Operating Temperature	32 to 104 °F (0 to 40 °C)				
Input Voltage	120 / 230* VAC ±10%, 47-63 Hz				
Dimension (W x H x D)	19" x 5.24" x 15.75" (483 x 133 x 400 mm)				
<b>Two-Year Warranty</b>					
Supplied Accessories	User manual and power cord				

\*230 VAC input requires modification that should be requested at time of order.



Technical data subject to change  
© B&K Precision Corp. 2013  
v020613

Contact:  
Industrial Process Measurement, Inc.  
3910 Park Avenue, Unit 7  
Edison, NJ 08820  
732-632-6400  
support@instrumentation2000.com  
<http://www.instrumentation2000.com>